Winner Pro 3P/1P



- True double-conversion
- Output power factor 0.8
- Wide input voltage range
- 50Hz frequency converter mode
- Emergency power off function (EPO)
- Generator compatible
- SNMP+USB+RS-232 multiple communications
- 3-stage extendable charging design for optimized battery performance
- Optional maintenance bypass switch
- Supports 3P/1P & 1P/1P operation

Winner Pro 3-phase in/1-phase out Online UPS Selection Guide

PHASE 3 phase in / 1 phase out CAPACITY 10000 VA / 8000 W 15000 VA / 12000 W 20000 VA / 1600 INPUT Nominal Voltage 3 x 400 VAC (3Ph+N) Voltage Range 190-520 VAC (3-phase) @ 50% load 305-520 VAC (3-phase) @ 100% load Frequency Range 46-54 Hz OUTPUT Output Voltage 208/220/230/240VAC AC Voltage Regulation (Batt. Mode) ± 1% Frequency Range (Synchronized Range) 46-54Hz Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)		
Nominal Voltage 3 x 400 VAC (3Ph+N)		
Nominal Voltage 3 x 400 VAC (3Ph+N) Voltage Range 190-520 VAC (3-phase) @ 50% load 305-520 VAC (3-phase) @ 100% load Frequency Range 46-54 Hz OUTPUT Output Voltage 208/220/230/240VAC AC Voltage Regulation (Batt. Mode) ± 1% Frequency Range (Synchronized Range) 46~54Hz Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)	00 W	
Voltage Range 190-520 VAC (3-phase) @ 50% load 305-520 VAC (3-phase) @ 100% load Frequency Range 46~54 Hz OUTPUT Output Voltage 208/220/230/240VAC AC Voltage Regulation (Batt. Mode) ± 1% Frequency Range (Synchronized Range) 46~54Hz Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)		
Voltage Range 305-520 VAC (3-phase) @ 100% load Frequency Range 46~54 Hz OUTPUT 0000 Voltage Output Voltage 208/220/230/240VAC AC Voltage Regulation (Batt. Mode) ± 1% Frequency Range (Synchronized Range) 46~54Hz Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)		
OUTPUT Output Voltage 208/220/230/240VAC AC Voltage Regulation (Batt. Mode) ± 1% Frequency Range (Synchronized Range) 46~54Hz Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)		
Output Voltage 208/220/230/240VAC AC Voltage Regulation (Batt. Mode) ± 1% Frequency Range (Synchronized Range) 46~54Hz Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)		
AC Voltage Regulation (Batt. Mode) ± 1% Frequency Range (Synchronized Range) 46~54Hz Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)		
Frequency Range (Synchronized Range) 46~54Hz Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)		
Frequency Range (Batt. Mode) 50 Hz ± 0.1 Hz Current Crest Ratio 3:1 (max.)		
Current Crest Ratio 3:1 (max.)		
Harmonic Distortion $\leq 3 \%$ THD (Linear Load); $\leq 5 \%$ THD (Non-linear Load)		
Transfer AC Mode to Batt. Mode Zero		
Time Inverter to Bypass Zero		
Waveform (Batt. Mode) Pure Sinewave		
EFFICIENCY		
AC Mode 91% 91% 91%		
Battery Mode 91% 91% 91%		
BATTERY		
Battery Type 12 V / 9 AH		
Numbers 16 pcs 20 pcs 16 pcs 20 pcs 16 pcs x 2 strings 20	pcs x 2 strings	
Standard Model Typical Recharge Time 9 hours recover to 90% capacity		
	1A/2A/4A ± 10% (2A default)	
Charging Voltage 218.4 VDC ± 1% 273 VDC ± 1% 218.4 VDC ± 1% 273 VDC ± 1% 218.4 VDC ± 1% 273 VDC ± 1% 218.4 VDC	73 VDC ± 1%	
Battery Type Depending on the capacity of external batteries		
Long-run Numbers 16 pcs 20 pcs 16 pcs 20 pcs 16 pcs	20 pcs	
Model Charging Current (max.) 4A Default, 1A/2A/4A (Adjustable)		
	73 VDC ± 1%	
INDICATORS		
LCD Panel UPS status, Load level, Battery level, Input/Output voltage, Discharge timer, and Fault conditions		
ALARM		
Battery Mode Sounding every 4 seconds		
Low Battery Sounding every second		
Overload Sounding twice every second		
Fault Continuously sounding		
PHYSICAL		
Standard Dimension, D x W x H mm) 442 x 190 x 688 442 x 190 x 688 815 x 250x 8:	26	
Model Net Weight (kgs) 66 76 67 78 125	145	
Long-run Dimension, D x W x H (mm) 442 x 190 x 318 575 x 190 x 3	118	
Model Net Weight (kgs) 15 16 18.95		
ENVIRONMENT		
Operating Humidity 0-95 % RH @ 0- 50°C (Non-condensing)		
Noise Level Less than 60dB @ 1 Meter		
MANAGEMENT		
Smart RS-232 / USB Supports Windows® 2000/2003/XP/Vista/2008, Windows® 7/8/10, Linux and MAC		
Optional SNMP Power management from SNMP manager and web browser		
Product specifications are subject to change without further notice.		

